

VOLT AMPS

Watts / Power Factor = Volt Amps

LOW VOLTAGE	Watt	Power Factor	Volt Amps (VA)
Micro G4	1.2	0.79	1.52
Micro T5	1.2	0.79	1.52
Beacon G4	2	0.61	3.28
Beacon Plus G4	3	0.66	4.55
Beacon T5	2	0.61	3.28
Beacon SCB	2	0.61	3.28
Beacon DCB	2	0.61	3.28
Beacon S8	2	0.61	3.28
G4 Ecostar	2	0.60	3.33
	3	0.60	5.00
T5 Ecostar	3	0.60	5.00
SCB Ecostar	3	0.60	5.00
Blaze G4	2	0.60	3.33
Rectangle Wafer	2	0.60	3.33
	3	0.58	5.10
Round Wafer	2	0.60	3.33
MR8	1.5	0.60	2.50
MR11	2	0.60	3.33
AR11	2	0.60	3.33
MR16 Ecostar	4	0.63	6.35
	7	0.63	11.11
MR16	4	0.63	6.35
	5	0.60	8.33
	7	0.63	11.11
PAR36	4	0.60	6.67
	7	0.65	10.77
	11	0.69	15.94
	15	0.70	21.43
Chameleon G4	2.5	0.60	4.17
Chameleon MR16	6	0.65	9.23
Chameleon PAR36	9	0.65	13.85
Strip Light	1.8	0.60	3.00 per ft
Wave Strip Light	4.5	1.5	2.50 per ft
Candelabra Edge Filament	2	0.85	2.35
	3.5	0.85	4.12
S14 Edge Filament	1	0.75	1.33
	2	0.75	2.67
	3.5	0.89	3.93
Light Bar 7.5" in Cascades	1.5	0.90	1.67
Light Bar Small	1.5	0.90	1.67
Light Bar Medium	2.5	0.90	2.78
Light Bar Large	4	0.91	4.40
Aquabeam	5	0.73	6.85
	10	0.88	11.36
Niche Light	3	0.60	5.00
Mini Beam 90	1.5	0.60	2.50
Mini Beam 200	3	0.80	3.75
Mini Beam 400 & Mount Rainier	6	0.65	9.23
Guadalupe	3.8	0.63	6.03
Versa Beam	3	0.63	4.78

LINE VOLTAGE	Watt	Power Factor	Volt Amps (VA)
S14 Edge Filament	2.5	0.90	2.78
	3.5	0.90	3.89
Candelabra Edge Filament	3.5	0.90	3.89
A19 Edge Filament	6.5	0.90	7.22
Blaze Candelabra	3	0.80	3.75